


Installation Guide For XN-2523G (XN-2522G w/FCC ID: MQ4WWMG2K4) **Software Version 7.0.1.33**

****ALWAYS OBTAIN THE LATEST DRIVER/UTILITY/FIRMWARE AT WWW.XTERASYS.COM****

- Download the latest driver from www.xterasys.com, and save it to a known location, such as Windows' desktop
- After download, double-click the file to open it, then **Unzip** the file to a known location, by default, it is unzipped to `c:\xterasys`

Wireless LAN Utility

Windows 98SE/ME/2000/XP

1. Uninstall any older version of Driver/Utility in the system before updating:
 - a. **Start**
 - b. **Programs** or **All Programs**
 - c. **802.11g...** or **WLANUtility...**
 - d. **Uninstall...**
 - e. Follow the instructions on screen, then click **Cancel** to avoid reboot
 - f. Shutdown the system, then remove the wireless card
 - g. Restart system
2. Go to the unzipped folder, by default, it is at `C:\Xterasys\xn2423g2523G_7_0_1_33`
3. Go to **Utility** folder, then double-click **Setup.exe**,  Setup
4. Follow through the installation process

Driver

Windows 98SE/ME

1. Shutdown the PC
2. Insert XN-2523G into an available PCI slot
3. Turn on the PC
4. Upon startup, Windows should automatically install the driver, but it may ask for Windows 98SE CD, please have it handy
5. In case Windows prompts for driver, please direct Windows to the **Driver** folder from the download, by default, it is at `C:\Xterasys\xn2423g2523G_7_0_1_33\Driver`
6. Restart the system after everything is done
7. Use the **Wireless LAN Utility** to configure the wireless card

Windows 2000

1. Shutdown the PC
2. Insert XN-2523G into an available PCI slot
3. Turn on the PC
4. Upon startup, a **Found New Hardware Wizard** screen will appear, click **Next**
5. An **Install Hardware Device Drivers** screen will appear, choose **Search for a suitable driver for my device (Recommended)**, click **Next**
6. Choose **Specify the Location**, click **Next**

Installation Guide For XN-2523G (XN-2522G w/FCC ID: MQ4WVG2K4) Software Version **7.0.1.33**

7. Click **Browse**, then direct Windows to the unzipped folder, by default, it is at **C:\Xterasys\xn2423g2523G_7_0_1_33**
8. Go to **Driver** folder, select the **TNET1130.INF** file, click **OK**
9. Windows 2000 will recognize the new device and the location of the driver in the **Drivers Files Search Results** window, click **Next** to install driver
10. Click **Yes** to continue. Finally, click the **Finish** to complete driver installation.
11. Restart the PC
12. Use the **Wireless LAN Utility** to configure the wireless card

Windows XP

1. Shutdown the PC
2. Insert XN-2523G into an available PCI slot
3. Turn on the PC
4. If **Found New Hardware Wizard** window comes up, go to step 5, otherwise do the following:
 - a. **Start** -> right-click on **My Computer** -> **Properties** -> **Hardware** -> **Device Manager**
 - b. Find the wireless card, which should show up as **Network Controller** with exclamation mark, or **802.11g...** under **Network adapters**
 - c. Right-click on the wireless card, and choose **Update Driver**
5. Choose **Install the software automatically (Recommended)**, then click **Next**



6. Click **Finish** when done
7. Reboot the PC
8. Use **Wireless LAN Utility** to configure the wireless card